



## INSTALLATION INSTRUCTIONS

1. Remove the cover plate from the appropriate option slot in the ATLAS 550 Base Unit.
2. Slide the Ethernet Switch Option Module into the option slot until the module is firmly positioned against the front of the chassis.
3. Secure the thumbscrews at both edges of the module. Tighten with a screwdriver.
4. Connect the cables to the associated device(s).
5. Complete installation of remaining modules and Base Unit as specified in the Installation chapter of the ATLAS 550 System Manual.

## NETWORK CONNECTION PINOUT

Pin	Name	Description
1	TX1	Transmit Positive
2	TX2	Transmit Negative
3	RX1	Receive Positive
4, 5	UNUSED	—
6	RX2	Receive Negative
7, 8	UNUSED	—

## SPECIFICATIONS

<b>Interface Type:</b>	(8) 10BaseT/100BaseTX interfaces with auto MDI/MDIX crossover on all interfaces
<b>Flow Control:</b>	Back-pressure flow control on all half-duplex interfaces Pause-frame flow control on full-duplex interfaces
<b>Environmental Specifications:</b>	Operating Temperature: 0°C to 45°C Storage Temperature: -20°C to 70°C Relative Humidity: Up to 95% non-condensing
<b>Compliance:</b>	FCC Part 15, Class A UL 60950, 3rd Edition EN 60950 ETSI 300 386

**MENU TREE**

